

Excelog 6 Modbus over serial line interface

Interface

COM port	Assigned on installation
Slave address	1
Baud rate	57600
Format	8 data, No parity, 2 stop
Reply delay (ms)	20 max

Supported functions

Read register	0x03, 0x04
---------------	------------

Address table

<u>Address</u>	<u>Description</u>	<u>Data type</u>	<u>Array size</u>
0x1000	Unfiltered temperature ¹	Int32	6
0x100C	Differential temperature ¹	Int32	6
0x1018	Cold junction temperature ¹	Int32	4
0x1020	Voltage (μ V)	Int32	4
0x1028	Resistance (m Ω)	Int32	2
0x102C	Maximum temperature ¹	Int32	6
0x1038	Minimum temperature ¹	Int32	6
0x1044	Average temperature ¹	Int32	6
0x1050	Standard deviation ²	Int32	6
0x105C	Alarm 1 status 0 = Alarm 1 not triggered 1 = Alarm 1 triggered	UInt16	6
0x1062	Alarm 2 status 0 = Alarm 2 not triggered 1 = Alarm 2 triggered	UInt16	6
0x1068	Channel type 0 = Type K 1 = Type J 2 = Type T 3 = Type N 4 = Type E 5 = Type R 6 = Type S 7 = PT100 2-wire 8 = PT200 2-wire 9 = PT500 2-wire 10 = PT1000 2-wire 11 = PT100 3-wire 12 = PT200 3-wire 13 = PT500 3-wire 14 = PT1000 3-wire	UInt16	6
0x106E	Units 0 = °C, 1 = °F	UInt16	1

¹ Least significant bit is 0.1, units specified by "Units" register

² Least significant bit is 0.001, units specified by "Units" register

For further information please refer to <http://www.modbus.org/specs.php>

For FTDI drivers please visit <http://www.ftdichip.com/FTDrivers.htm>